

No port forwarding or DynDNS is required for Internet access to our devices. Please do not set up port forwarding for our devices, as this reduces the security of your network.

Device (IP Video Door Station) - Ports and protocols

| Port | Protocol | Network | Remark |
|-------|----------|-----------------------------|--------------------------------------|
| 80 | TCP | LAN | For access via LAN |
| 80 | TCP | WAN (Ausgehende Verbindung) | For access via Internet |
| 443 | TCP | LAN | For access via LAN |
| 443 | TCP | WAN (Ausgehende Verbindung) | For access via Internet |
| 554 | TCP | LAN | HD-Video via LAN (D11x devices only) |
| 5353 | UDP | LAN | Bonjour |
| 6524 | UDP | LAN | Event Broadcast |
| 35344 | UDP | LAN | Event Broadcast |



The device establishes a secure, encrypted, direct and permanent connection to the Internet. We recommend a fixed broadband internet connection (without proxy or SOCKS servers) for operation. If you need to configure a domain in your firewall, please allow *.doorbird.net. We have numerous redundant servers in our data centers, so it is not possible to name specific IP addresses. Please note that communication on port 80 is also encrypted.

Mobile device - Ports and protocols

| Port | Protocol | Network | Remark |
|-------|----------|---------------------------|--------------------------------------|
| 80 | TCP | LAN | For access via LAN |
| 80 | TCP | WAN (Outgoing connection) | For access via Internet |
| 443 | TCP | LAN | For access via LAN |
| 443 | TCP | WAN (Outgoing connection) | For access via Internet |
| 2195 | TCP | WAN (Outgoing connection) | Apple Push Service |
| 2196 | TCP | WAN (Outgoing connection) | Apple Push Service |
| 5223 | TCP | WAN (Outgoing connection) | Apple Push Service |
| 5228 | TCP | WAN (Outgoing connection) | Google Push Service |
| 5229 | TCP | WAN (Outgoing connection) | Google Push Service |
| 5230 | TCP | WAN (Outgoing connection) | Google Push Service |
| 5352 | UDP | LAN | Bonjour |
| 6524 | UDP | LAN | Event Broadcast |
| 6999 | UDP | WAN (Outgoing connection) | For access via Internet |
| 8881 | UDP | LAN | HD Video via LAN (D11x devices only) |
| 8882 | UDP | LAN | HD Video via LAN (D11x devices only) |
| 35344 | UDP | LAN | Event Broadcast |

